



AUDIO PROCESSOR



TDFS-01

The TDFS-01 Feedback Suppressor is a high performance feedback DSP feedback suppressor designed around a powerful 28-/56-Bit Audio Processor Module. The unit is designed to be 'set and forget', with minimal hassle free settings required. With its ultra-fast attack time the unit automatically scans the input mix, eliminates the feedback and resets the programmed filters once it is done. Control of the unit is via Bluetooth, users can utilize the app to enable and disable the Feedback Suppressor function.

FEATURES

- Wireless control via Bluetooth 4.0 interface.
- Minimal setup and setting.
- Fully automated 'set and forget' mode of operation.
- Rack mountable.

Technical Specification

	TDFS-01
Audio Input	XLR Connector
Audio Output	XLR Connector
Bandwidth	20Hz – 20kHz
SNR	>90dB
THD	Less than 0.01%
DSP Converter	24-bit Sigma-Delta, 64/128-times Oversampling
DSP Sampling	46kHz
Control Interface	Bluetooth 4.0